

HSIB1000

HIGH EFFICIENCY 1000 KW CENTRAL INVERTER

The photovoltaic central inverter HSIB1000 is a special transformerless development for IT-grids and for the operation with the String Booster Box SBB16-10. The inverter was designed using the newest efficiency-optimized technology in order to get higher returns from the solar installation. Right from the start, all devices to be installed were chosen with respect to loss reduction:

- The power part was realized using Trench-IGBTs of the newest generation and intentionally oversized to increase efficiency.
- The filter inductor was optimized to reduce power losses under partial as well as full load condition.
- Large heat sinks allow the use of small fans with low power consumption.
- Motor driven DC-breakers are used.

The sum of these measures leads to a maximum efficiency of 98,7 %. Even under partial load of only 10 % an efficiency of 98,6 % is achieved. The EU efficiency reaches outstanding 98,7 %. This high efficiency is unique for inverters of this technology and offers multiple advantages to the user:

- More energy from the photovoltaic array is fed to the grid, therefore a higher rate of return is obtained.
- Less waste heat has to be dissipated out of the already warm operating room.
- The reduction of losses increases the lifetime of the internal components.

The system is designed for low maintenance and long lifetime. Within the development process of the HSIB1000, a major design criterion was the simpleness and safety of the operating system for the inverter. This was achieved by a touch screen with a menu-based graphic user interface. Up to one year, the inverter stores all relevant measured values. These values as well as current operating data can be monitored online or downloaded via the Ethernet interface. In the unlikely case of an inverter fault, the control software automatically sends a message with a failure report. The inverter operates completely stand-alone and the first start-up requires no adjustments of the system. Each string box can be connected and disconnected by a Scada system.



HSIB1000

Technical Data HSIB1000

Electrical Data

| | |
|--|--|
| Rated AC-power at $\pm 10\%$ of rated grid voltage | 1000 kW |
| Maximum AC-power at rated grid voltage | 1100 kW |
| AC-voltage and frequency range, other frequencies on request | 480 V $\pm 10\%$, 3~, 50 Hz ± 2 Hz, IT-grid |
| Maximum AC-current | 1323 A |
| Line power factor ($\cos \Phi$) at 20% rated power | > 0,98 |
| AC-current distortion (THD) at rated power | < 3 % |
| Rated PV-power within $\pm 10\%$ of rated grid voltage | 1014 kW |
| Maximum PV-power at rated grid voltage | 1117 kW |
| Maximum PV-current | 1363 A |
| Maximum PV no-load-voltage | 1000 V= |
| PV-rated voltage | 820 V= |
| Control strategy | Constant voltage |
| Efficiency at (10 30 50 75 100) % power | (98,6 98,8 98,8 98,7 98,6) |
| EU efficiency incl. auxiliary power without cooling circuit | 98,7 % |
| Feed-in starting at | 500 W |
| Standby losses | < 30 W |
| Maximum auxiliary power | < 2000 W |

General Data

| | |
|---|---|
| Ambient temperature (Others on request) | 0 °C to 50 °C |
| Relative humidity non-condensing | < 95 % |
| Cooling type | 1500 m above sea level |
| Minimum air quality acc. to EN60721-3-3 | Forced air cooling 3000 m ³ /h |
| Maximum altitude without derating in power | Class 3S2 |
| Protection class | IP20 |
| Dimensions (H x W x D) Inverter + control cabinet | 2100 mm x 1800 mm x 850 mm |
| Weight Inverter + control cabinet | 1700 kg |
| Colour of cabinet (different colours on request) | RAL7035 |
| EMI | Complies EN 6100-6-2, EN 61000-6-4 |
| Medium-voltage directive | CBDEW |
| Grid monitoring | Acc. to VDEW s/ BDEW tandards |
| CE-conformity | Complies |

Features

| | |
|-------------------------|------------------------------------|
| DC-disconnector | - |
| AC-contactor | Grid contactor |
| AC circuit breaker | Available |
| Earth leakage detection | Earth leakage monitor |
| Surge arresters | With monitoring on AC- and DC-side |

Options

| | |
|---|---|
| Earthing of solar array | Only negative pole |
| Separately secured DC-inputs | Heating incl. thermostat |
| Measuring and monitoring of single input currents | |
| Sensor (interface for radiation sensor => features) | |
| Cabinet heating incl. thermostat | |
| Display in control cabinet for status display | Touch screen with numerical and graphical display |
| Communication Cabinet Standard | PC and monitor |