

FLOOR MOUNTED LIFEP04 BATTERY DATASHEET (51. 2V400Ah)

(Specifications)

2024. 04. 10

| No. | Items | | Value |
|-----|----------------------------------|-------------------------|---|
| 1 | Cell | | 3.2V 400AH |
| 2 | Pack Style | | 16S1P |
| 3 | Nominal Voltage | | 48V |
| 4 | Nominal Capacity | | 400Ah |
| 5 | Min Capacity | | 400Ah |
| 6 | Rated Power | | 15KWh |
| 7 | Charging Voltage | | 57.6V |
| 8 | Working Voltage | | 40V~58.4V |
| 9 | Cycle Life | | ≥6000 times |
| 10 | Charging Current | Standard Charge Current | 50A (0°C~10°C) |
| | | Max Charge Current | 200A (10°C~45°C) |
| 12 | Max Continuous Discharge Current | | 200A |
| 13 | Internal Resistance | | ≤100mΩ |
| 14 | Dimension L*W*H/mm | | 913*590*265 mm (Excluding terminal blocks) |
| 15 | Approx. Weight | | ≈150Kg (Estimating weight) |
| 16 | Operating Temperature | Charge | 0°C~55°C |
| | | Discharge | -20°C~60°C |
| 17 | Storage Temperature | 1 month | -0°C~45°C |
| | | 3 months | -0°C~35°C |
| | | 6 months | -0°C~25°C |

2、 Protection functions

The battery is packed with the protection circuit module (PCM) , which can ensure the safety of this battery in charging and discharging.

The main functions of the BMS are as follows:

- 1) Over charge protection;
- 2) Over discharge protection;
- 3) Temperature protection;
- 4) Overcurrent protection;
- 5) Software protection board with RS485/RS232/CAN communication function, supporting up to 16pcs parallel use, and supporting communication with inverters
- 6) Equipped with a 3-inch blue screen (touch screen), 6A soft switch
200A through type terminal,

3、 Drawing

Dimensions: L913*W590*H265mm






Bluetooth Function

Search PACEES BMS On the iPhone Store to

Download And Follow the next step

[]





Equipment control and data display

The APP has completed the summary interface, including basic data, voltage and temperature, status data, historical data, parameter settings, device information, and general settings



OTA upgrade

The original design of the upgrade triggering strategy was for the APP to automatically identify whether an upgrade was needed based on the current software version number of the device. However, due to incorrect responses to MCU software version and other information, it was temporarily triggered by clicking on the device icon.

7.1: On the device list page, click on the device icon and a window will pop up for entering the firmware security code

7.2: Based on the security code entered by the user, pull the firmware information corresponding to the server and confirm the upgrade

