

Energrid VII WP Series

- Pure sine wave output
- IP65 waterproof and dustproof makes the inverter available for various working conditions.
- Self-consumption and Feed-in to the grid
- Programmable supply priority for PV, Battery or Grid
- Reserved communication port for BMS (RS485)
- User-adjustable charging current and voltage
- Programmable multiple operation modes: Grid-tie, off-grid and grid-tie with backup
- Monitoring software for real-time status display and control
- Parallel operation up to 9 units



Specifications

MODEL	Energrid V II WP 2KM-48	Energrid V II WP 3KM-48	Energrid V II WP 5KM-48	Energrid V II WP 6KM-48
Phase	1-phase in / 1-phase out			
Maximum PV Input Power	3000 W	4500 W	6000 W	6500 W
Rated Output Power	2000VA/2000W	3000VA/3000W	5000VA/5000W	6000VA/6000W
Maximum Charging Power	2000 W	3000 W	4000 W	6000 W
GRID-TIE OPERATION				
PV INPUT (DC)				
Maximum DC Voltage	400 VDC	500 VDC	500 VDC	550 VDC
Start-up Voltage / Initial Feeding Voltage	120VDC / 150 VDC			
MPP Voltage Range	120 VDC ~ 400 VDC	120 VDC ~ 450 VDC	120 VDC ~ 450 VDC	120 VDC ~ 450 VDC
Number of MPP Trackers / Maximum Input Current	1 / 13A	1 / 18A	1 / 27A	1 / 27A
GRID OUTPUT (AC)				
Nominal Output Voltage	220/230/240 VAC			
Output Voltage Range	184 - 264.5 VAC or 195.5 - 253 VAC (Selectable)			
Nominal Output Current	8.7A	13A	21.7A	26A
Power Factor	> 0.99			
EFFICIENCY				
Maximum Conversion Efficiency (DC/AC)	95%			96%
OFF-GRID OPERATION				
AC INPUT				
AC Start-up Voltage / Auto Restart Voltage	120 - 140 VAC / 180 VAC			
Acceptable Input Voltage Range	90 - 280 VAC or 170 - 280 VAC			
Frequency Range	50 Hz/60 Hz (Auto sensing)			
Maximum AC Input Current	20 A	30 A	40 A	40 A
PV INPUT (DC)				
Maximum DC Voltage	400 VDC	500 VDC	500 VDC	550 VDC
MPP Voltage Range	120 VDC ~ 400 VDC	120 VDC ~ 450 VDC	120 VDC ~ 450 VDC	120 VDC ~ 450 VDC
Number of MPP Trackers / Maximum Input Current	1 / 13A	1 / 18A	1 / 27A	1 / 27A
BATTERY MODE OUTPUT (AC)				
Nominal Output Voltage	220/230/240 VAC			
Output Waveform	Pure sine wave			
Efficiency (DC to AC)	93%			
HYBRID OPERATION				
PV INPUT (DC)				
Maximum DC Voltage	400 VDC	500 VDC	500 VDC	550 VDC
Start-up Voltage / Initial Feeding Voltage	120 VDC / 150 VDC			
MPP Voltage Range	120 VDC ~ 400 VDC	120 VDC ~ 450 VDC	120 VDC ~ 450 VDC	120 VDC ~ 450 VDC
Number of MPP Trackers / Maximum Input Current	1 / 13A	1 / 18A	1 / 27A	1 / 27A
GRID OUTPUT (AC)				
Nominal Output Voltage	220/230/240 VAC			
Output Voltage Range	184 - 264.5 VAC or 195.5 - 253 VAC (Selectable)			
Nominal Output Current	8.7A	13A	21.7A	26A
AC INPUT				
AC Start-up Voltage / Auto Restart Voltage	120 - 140 VAC / 180 VAC			
Acceptable Input Voltage Range	90 - 280 VAC or 170 - 280 VAC			
Maximum AC Input Current	20 A	30 A	40 A	40 A
BATTERY MODE OUTPUT (AC)				
Nominal Output Voltage	220/230/240 VAC			
Efficiency (DC to AC)	93%			
BATTERY & CHARGER				
Nominal DC Voltage	48 VDC			
Maximum Solar Charging Current	40 A	60 A	100 A	120 A
Maximum AC Charging Current	40 A	60 A	100 A	120 A
Maximum Charging Current	40 A	60 A	100 A	120 A
GENERAL				
PHYSICAL				
Dimension, D x W x H (mm)	200 x 360 x 665			
Net Weight (kgs)	22.5			
INTERACE				
Parallel Function	Yes, 9 units			
Communication Port	USB or RS-232 / Dry Contact/RS485			
ENVIRONMENT				
Humidity	0 ~ 95% RH (No condensing)			
Operating Temperature	-25°C to 50°C			

Product specifications are subject to change without further notice.

Ver1.0_21.2.2023

Authorised Distributor/ Reseller:

Compatible with:



Prolink is a registered trademark of Fida International (S) Pte Ltd. Other brands and product names are trademarks or registered trademarks of their respective holders. Product images are purely for illustrative purposes and may differ from the actual product. Specifications are subjected to changes without prior notice. Copyright © 2023 Fida International (S) Pte Ltd.