



MODIFIED SINE WAVE INVERTER



SMALL MODIFIED sine wave inverters (175 - 600 watts)



GP-600

GP-175

GP-300

Simply plug the item you wish to run into one of the AC receptacles.

GP-300 and GP-175 models simply plug into any 12 volt accessory socket.

GP-600 / GP-300 / GP-175

Run standard AC appliances wherever you travel. Silent, lightweight and easy to use, Go Power! Inverters bring electricity to your RV, boat, truck or even your home in the event of a power failure. With an inverter, your AC loads run off your batteries and they can be used any time of day or night - without a generator.

- Powerful and economical
- Light-weight and compact
- Thermal and overload protection
- Low voltage alarm shutdown
- Retail ready packaging
- 1 year warranty

GP-175	✓	✓	✓	✓		
GP-300			✓	✓	✓	
GP-600				✓	✓	✓

*B/C = battery charging
Review individual product specs for actual wattage requirements

SPECIFICATIONS*	GP-175	GP-300	GP-600
Continuous Wattage	175W	300W	600W
Surge Rating	210W	400W	860W
Output Waveform	Modified Sine Wave		
Output Voltage	110 VAC RMS +5% / -10%		
Output Frequency +-1%	60 Hz		
Input Voltage	10.5 -15 VDC		
Efficiency	80-90%		
No Load Current Draw	0.2 A		
Protection	Overload, over-temperature, over-voltage and low voltage		
Low Battery Alarm +-2%	10.5 V		
Low Battery Shut-down +-2%	10.0 V		
Operating Temp.Range	0 – 40 C / 32 – 104 F		
Storage Temp.Range	-30 – 70 C / -22 – 158 F		
Cooling	Passive	Continuous fan	Continuous fan
AC Receptacle	1	2	2
(LxWxH) mm	135 x 53 x 46	165 x 89 x 51	229 x 86 x 51
inches	5.3 x 2.1 x 1.8	6.5 x 3.5 x 2	9 x 3.4 x 2
Weight (kg/lbs)	0.5 / 1.1	0.8 / 1.8	2.1 / 4.6
Warranty	1 year		
Inverter Install Kit	Auto utility adaptor	Auto utility adaptor	Spring clamp

*Specifications subject to change without notice