

## TECHNICAL CHARACTERISTICS

## HEM HYBRID

REFERENCE	FS3510M2	FS3510M4	FS3510M6
<b>OUTPUT</b>	AC Output Power (kVA/kW) @50°C [1]	3510	
	AC Output Power (kVA/kW) @40°C [1]	3630	
	Operating Grid Voltage	34.5 kV ±10 %	
	Operating Grid Frequency	60Hz	
	Current Harmonic Distortion (THDI)	< 3% per IEEE 519	
<b>INPUT</b>	Power Factor (cosine phi) [2]	0.5 leading ... 0.5 lagging adjustable / Reactive Power injection at night	
	MPPt @full power	934V - 1310V	
	Maximum DC voltage	1500V	
	Number of PV inputs [3]	Up to 36	
	Number of Freemaq DC/DC	2	4
	Freemaq DC/DC Power (kW) @50°C	1000	2000
	DC ESS Voltage range [4]	700V - 1500V	
<b>EFFICIENCY &amp; AUXILIARY SUPPLY</b>	Max. DC continuous current (A) [5]	6200	
	Max. DC short circuit current (A) [5]	12000	
	Max. PV Inverter Efficiency PAC, nom (η)	97.80% including MV transformer (preliminary)	
<b>CABINET</b>	CEC PV Inverter Efficiency (η)	97.51% including MV transformer (preliminary)	
	Max. Power Consumption (kVA)	30	
	Dimensions [WxDxH] (ft)	30.38 x 7 x 7 (preliminary)	
	Dimensions [WxDxH] (m)	9.26 x 2.2 x 2.2 (preliminary)	
	Weight (lb)	< 41888	
<b>ENVIRONMENT</b>	Weight (kg)	< 19000	
	Type of ventilation	Forced air cooling	
	Degree of protection	NEMA 3R	
	Permissible Ambient Temperature	-35°C to +60°C / > 50°C Active Power derating	
	Relative Humidity	4 % to 100 % non condensing	
<b>CONTROL INTERFACE</b>	Max. Altitude (above sea level) [6]	2000 m	
	Noise level [7]	< 79 dBA	
	Communication protocol	Modbus TCP	
<b>PROTECTIONS</b>	Plant Controller Communication	Optional	
	Keyed ON/OFF switch	Standard	
	Ground Fault Protection	GFDI and isolation monitoring device	
	General AC Protection	MV switchgear (configurable)	
<b>CERTIFICATIONS</b>	General DC Protection	Fuses	
	Overshoot Protection	Type 2	
	Safety	UL 1741, CSA 22.2 No.107.1-16	
	Compliance	NEC 2017	
	Utility interconnect	IEEE 1547.1-2005 / UL 1741 SA - Feb. 2018	

[1] Values at 1.00×Vac nom and cos Φ= 1. Consult Power Electronics for derating curves.

[2] Consult P-Q charts available: Q(kVar)=V(S(kVA)²-P(kW)²).

[3] Consult Power Electronics for other configurations.

[4] Consult Power Electronics for derating curves.

[5] Consult Power Electronics for higher currents.

[6] Consult Power Electronics for other altitudes.

[7] Readings taken 1 meter from the back of the unit.