



MODIFY SINE WAVE INVERTER 3000W

| | |
|---|---|
| Model | 3000W- OREX |
| Rated output voltage | 12V-220V |
| Output Wave Form | Modified Sine Wave Output |
| Output Frequency | 50/60Hz |
| LED display | input state,output state , working state |
| Resistive full load efficiency | 88% |
| Rated input voltage | 12VDC |
| rated input voltage range | 10.5-15.5VDC |
| No Load Current Draw | <0.5A |
| input Over voltage/battery low voltage | output shutdown makes the voltage back to normal, and then the inverter automatically starts. |
| overload , short circuit,over current ,over heat protection | Make Output shutdown and restart |
| input reverse polarity | short circuit protection D |
| Rated output | 3000w |
| Peak Output | 6000w |



ARWA RAZOUK ELECTRONICS LLC DUBAI, UAE

www.orexpower.com

info@orex-ae.com

+971502244390 / +97145461772