## **LEONICS**®

# LEONICS. · www.leonics.com ·

Wall Mount Enclosure






Rack Mount 2U Enclosure with LED display

## **SOLARCON SCO**

### MPPT Charge Controller

- Advanced microprocessor control
- Maximum Power Point Tracking (MPPT)
- Buck regulator wide input range
- 3-step charging to provide quick and safe charging for battery
- Compatible with sealed lead acid (default), lead acid, Li-Ion (NMC, LFP) and SoNick batteries
- PV and battery reverse polarity protection
- Over charge and over discharge protection
- Lightning surge protection
- PV ground fault protection (option)
- Automatic cooling fan (outside enclosure)
- Comprehensive LED indication and LCD display
- Power and event data logger
- IP30 protection enclosure (IP31 protection enclosure is optional)
- 2 years warranty (option for 3 and 5 years)
- ISO 9001, ISO 14001 and ISO 45001 certified factory



The SOLARCON SCO-series charge controller is the most sophisticate solar charger with PV Maximum Power Point Tracking (MPPT) algorithm. The charge controller equipped with advanced microprocessor control to get the maximum power from PV to charge battery with LCD display and front panel for easy and accurate setting more over the digital meter with 180 days power and event logger are inclusive.





### **SOLARCON SCO-series** MPPT Charge Controller

	Wall mount (WM)	SCO-4860	SCO-4880	SCO-48120
	Rack mount (RM)	SCO-4860/RM	SCO-4880/RM	SCO-48120/RM
NPUT (C	onfiguration of PV in s	eries within these voltage range)		
mp of P	<b>V</b> *		88 - 126 Vdc	
Maximum Voc of PV*		150 Vdc		
Maximum PV power**		3.3 kWp	4.4 kWp	6.6 kWp
Number o	of PV input WM	1 x Terminal	1 x Terminal	2 x Terminal
	RM	3 x MC4 or 1 x termnal	3 x MC4 or 1 x termnal	4 x MC4 or 1 x termnal
Max. PV current		50 A	75 A	100 A
Max. current (Isc) per MC4			30 A	
	(at 25°C)			
Nominal battery voltage		48 Vdc		
Boost charging voltage		52.0 - 60.0 Vdc (default = 56.4 Vdc)		
Float charging voltage		48.0 - 56.0 Vdc (default = 54.0 Vdc)		
Voltage regulation		± 0.5 V (steady load)		
Low voltage alarm		40.0 - 48.0 Vdc (default = 46 Vdc)		
Low battery voltage		39.6 - 47.6 Vdc (default = 43.2 Vdc)		
disconne	cted		,	
Reconne	ct voltage		46.0 - 54.0 Vdc (default = 50.0 Vdc)	
	n charging current	60 A	80 A	120 A
BATTER\			5511	12011
уре		Sealed lead acid (VRLA) (	default), Deep cycle lead acid (LA), L	i-Ion (NMC, LFP), SoNick
FFICIEN	ICY	, (	,	-, ,,
Charger peak efficiency		> 98.6%		
MPPT efficiency		> 99%		
ROTEC				
Protectio	-	PV and battery reverse polari	ity, High battery voltage, Low battery	voltage. Over temperature.
			e, PV ground fault (option), PV transi	
NDICATO				
	OR		e, g	one voltage dange (option)
	OR		evel, PV voltage level, Operation statu	
_ED	OR	Battery le	evel, PV voltage level, Operation statu	us, Alarm
.ED .CD	OR  NICATION INTERFACE	Battery le Digita		us, Alarm
LED LCD COMMUI		Battery le Digita	evel, PV voltage level, Operation statu	us, Alarm ogger
ED CD COMMUI Selectabl	NICATION INTERFACE	Battery le Digita RS-485	evel, PV voltage level, Operation statu I meter, 180 days power and event lo (default) or RS-232 for WM, RS-485	us, Alarm ogger for RM
ED COMMUI Selectabl Ory conta	NICATION INTERFACE le by setting act signal	Battery le Digita RS-485	evel, PV voltage level, Operation statu I meter, 180 days power and event lo	us, Alarm ogger for RM
ED COMMUI Selectabl Dry conta	NICATION INTERFACE le by setting act signal	Battery le Digita E RS-485 Charge	evel, PV voltage level, Operation statu I meter, 180 days power and event lo (default) or RS-232 for WM, RS-485 er fail and low battery voltage discont	us, Alarm ogger for RM nected
ED COMMUI Selectabl Ory conta SYSTEM Control	NICATION INTERFACE le by setting act signal	Battery le Digita E RS-485 Charge	evel, PV voltage level, Operation statuder, 180 days power and event located (default) or RS-232 for WM, RS-485 er fail and low battery voltage discontioning fan, Maximum Power Point Tra	us, Alarm ogger for RM nected
ED COMMUI Selectabl Ory conta SYSTEM Control Femp. co	NICATION INTERFACE le by setting act signal empensation range	Battery le Digita E RS-485 Charge	evel, PV voltage level, Operation statu I meter, 180 days power and event lo (default) or RS-232 for WM, RS-485 er fail and low battery voltage discont	us, Alarm ogger for RM nected
ED COMMUI Selectabl Ory conta SYSTEM Control Temp. co	NICATION INTERFACE le by setting act signal empensation range	Battery le Digita RS-485 Charge Automatic cod	evel, PV voltage level, Operation statudent in meter, 180 days power and event level (default) or RS-232 for WM, RS-485 er fail and low battery voltage disconsioning fan, Maximum Power Point Trace-5 to 7 mV / cell / celsius (option)	us, Alarm ogger for RM nected cking (MPPT)
ED COMMUI Selectabl Ory conta SYSTEM Control Temp. co ENVIRON	NICATION INTERFACE le by setting act signal empensation range NMENT ture	Battery le Digita RS-485 Charge Automatic cod	evel, PV voltage level, Operation statudent meter, 180 days power and event located (default) or RS-232 for WM, RS-485 er fail and low battery voltage disconstoling fan, Maximum Power Point Tractor -5 to 7 mV / cell / celsius (option)	us, Alarm ogger for RM nected cking (MPPT)
ED COMMUI Selectabl Ory conta SYSTEM Control Temp. co ENVIRON Temperat	NICATION INTERFACE le by setting act signal empensation range NMENT ture numidity	Battery le Digita RS-485 Charge Automatic cod	evel, PV voltage level, Operation statudent in meter, 180 days power and event level (default) or RS-232 for WM, RS-485 er fail and low battery voltage disconsioning fan, Maximum Power Point Trace-5 to 7 mV / cell / celsius (option)	us, Alarm ogger for RM nected cking (MPPT)
ED COMMUI Selectabl Dry conta SYSTEM Control emp. co ENVIRON emperat Relative h	NICATION INTERFACE le by setting act signal empensation range NMENT ture numidity degree classification	Battery le Digita RS-485 Charge Automatic cod 0 - 50°C (Extended rai	evel, PV voltage level, Operation statuder and event level and event level and event level (default) or RS-232 for WM, RS-485 er fail and low battery voltage disconstant oling fan, Maximum Power Point Trace-5 to 7 mV / cell / celsius (option)  nge: 0 - 70°C) (Output characteristic 0 - 95% (non-condensing)	us, Alarm ogger for RM nected cking (MPPT)
ED COMMUI Selectabl Ory conta SYSTEM Control Temp. co ENVIRON Temperat Relative P Pollution Max. ope	NICATION INTERFACE le by setting act signal empensation range NMENT ture numidity degree classification eration altitude	Battery le Digita RS-485 Charge Automatic cod 0 - 50°C (Extended rai	evel, PV voltage level, Operation statuder, 180 days power and event level (default) or RS-232 for WM, RS-485 er fail and low battery voltage discontioning fan, Maximum Power Point Trace-5 to 7 mV / cell / celsius (option)  nge: 0 - 70°C) (Output characteristic 0 - 95% (non-condensing)	us, Alarm ogger for RM nected cking (MPPT)
ED COMMUI Gelectabl Ory conta SYSTEM Control Gemp. co ENVIRON Gemperat Relative h Collution Max. ope	NICATION INTERFACE le by setting act signal empensation range NMENT ture numidity degree classification eration altitude REGULATION	Battery le Digita RS-485 Charge Automatic cod 0 - 50°C (Extended rai	evel, PV voltage level, Operation statul meter, 180 days power and event level (default) or RS-232 for WM, RS-485 er fail and low battery voltage disconsional fan, Maximum Power Point Trace-5 to 7 mV / cell / celsius (option)  nge: 0 - 70°C) (Output characteristic 0 - 95% (non-condensing)  III  000 m / 6,560 feet (without derating)	us, Alarm ogger for RM nected cking (MPPT)
ED COMMUI Selectabl Ory conta SYSTEM Control Temp. co ENVIRON Temperat Relative I Pollution Max. ope DESIGN I	NICATION INTERFACE le by setting act signal empensation range NMENT ture numidity degree classification eration altitude REGULATION	Battery le Digita RS-485 Charge Automatic cod 0 - 50°C (Extended rai	evel, PV voltage level, Operation statul meter, 180 days power and event level (default) or RS-232 for WM, RS-485 or fail and low battery voltage disconsional fan, Maximum Power Point Trace-5 to 7 mV / cell / celsius (option)  nge: 0 - 70°C) (Output characteristic 0 - 95% (non-condensing)  III  000 m / 6,560 feet (without derating)  IEC 61683, IEC 62109-1	us, Alarm ogger for RM nected cking (MPPT)
COMMUI Selectable Ory conta SYSTEM Control Gemp. co SNVIRON Gemperat Relative P Pollution Max. ope DESIGN I Standard	NICATION INTERFACE le by setting act signal empensation range NMENT ture numidity degree classification eration altitude REGULATION	Battery le Digita RS-485 Charge Automatic cod 0 - 50°C (Extended rai	evel, PV voltage level, Operation statul meter, 180 days power and event level (default) or RS-232 for WM, RS-485 er fail and low battery voltage disconsional fan, Maximum Power Point Trace-5 to 7 mV / cell / celsius (option)  nge: 0 - 70°C) (Output characteristic 0 - 95% (non-condensing)  III  000 m / 6,560 feet (without derating)	us, Alarm ogger for RM nected cking (MPPT)
COMMUI Selectable Ory contact SYSTEM Control Femp. co ENVIRON Femperate Relative In Pollution Max. ope DESIGN In Standard Ingress protective	NICATION INTERFACE le by setting act signal empensation range NMENT ture numidity degree classification eration altitude REGULATION erotection e class	Battery le Digita  RS-485  Charge  Automatic cod  0 - 50°C (Extended rad)	evel, PV voltage level, Operation statul meter, 180 days power and event level (default) or RS-232 for WM, RS-485 or fail and low battery voltage disconsional fan, Maximum Power Point Trace-5 to 7 mV / cell / celsius (option)  nge: 0 - 70°C) (Output characteristic 0 - 95% (non-condensing)  III  000 m / 6,560 feet (without derating)  IEC 61683, IEC 62109-1	us, Alarm ogger  for RM nected  cking (MPPT)  derate above 50°C)
COMMUNICATION CONTROL	NICATION INTERFACE le by setting act signal ompensation range NMENT ture numidity degree classification eration altitude REGULATION orotection e class age category	Battery le Digita  RS-485  Charge  Automatic cod  0 - 50°C (Extended rad)  2,0	evel, PV voltage level, Operation statudent meter, 180 days power and event level (default) or RS-232 for WM, RS-485 er fail and low battery voltage disconstitution oling fan, Maximum Power Point Tractor -5 to 7 mV / cell / celsius (option)  Inge: 0 - 70°C) (Output characteristic 0 - 95% (non-condensing)  III  O00 m / 6,560 feet (without derating)  IEC 61683, IEC 62109-1  IP30 (IP31 is optional)	us, Alarm ogger  for RM nected  cking (MPPT)  derate above 50°C)
COMMUI Selectabl Ory conta SYSTEM Control Temp. co ENVIRON Temperat Relative h Pollution Max. ope DESIGN Standard Ingress p Protective Overvolta	NICATION INTERFACE le by setting act signal empensation range NMENT ture numidity degree classification eration altitude REGULATION erotection le class age category ON (W x H x D) (appro	Battery le Digita RS-485 RS-485 Charge Automatic cod 0 - 50°C (Extended rad 2,0  Il (input ar ximate in cm.)	evel, PV voltage level, Operation statul meter, 180 days power and event level (default) or RS-232 for WM, RS-485 er fail and low battery voltage disconsoling fan, Maximum Power Point Tra -5 to 7 mV / cell / celsius (option)  nge: 0 - 70°C) (Output characteristic 0 - 95% (non-condensing)  III  000 m / 6,560 feet (without derating)  IEC 61683, IEC 62109-1  IP30 (IP31 is optional)  Ind output) (in accordance with IEC 62	us, Alarm ogger  for RM nected  cking (MPPT)  derate above 50°C)
ED COMMUI Selectabl Ory conta SYSTEM Control Femp. co ENVIRON Selative h Pollution Max. ope DESIGN I Standard Ingress p Protective Overvolta Vall mou	NICATION INTERFACE le by setting act signal empensation range NMENT ture numidity degree classification eration altitude REGULATION erotection e class age category ON (W x H x D) (apprount case	Battery le Digita  RS-485 Charge  Automatic cod  0 - 50°C (Extended rad  2,0  II (input ar ximate in cm.)	evel, PV voltage level, Operation statul meter, 180 days power and event level (default) or RS-232 for WM, RS-485 or fail and low battery voltage disconstitution oling fan, Maximum Power Point Trace-5 to 7 mV / cell / celsius (option)  nge: 0 - 70°C) (Output characteristic 0 - 95% (non-condensing)  III  000 m / 6,560 feet (without derating)  IEC 61683, IEC 62109-1  IP30 (IP31 is optional)  Ind output) (in accordance with IEC 66)	us, Alarm ogger  for RM nected  cking (MPPT)  derate above 50°C)
COMMUI Selectabl Ory conta SYSTEM Control Femp. co ENVIRON Femperat Relative h Pollution Max. ope DESIGN of Control Overvolta DIMENSI Vall mou Rack mou	NICATION INTERFACE le by setting act signal  Impensation range NMENT ture Inumidity degree classification eration altitude REGULATION Intercetion e class age category ON (W x H x D) (apprount case unt case (2U)	Battery le Digita RS-485 RS-485 Charge Automatic cod 0 - 50°C (Extended rad 2,0  Il (input ar ximate in cm.)	evel, PV voltage level, Operation statul meter, 180 days power and event level (default) or RS-232 for WM, RS-485 er fail and low battery voltage disconsoling fan, Maximum Power Point Tra -5 to 7 mV / cell / celsius (option)  nge: 0 - 70°C) (Output characteristic 0 - 95% (non-condensing)  III  000 m / 6,560 feet (without derating)  IEC 61683, IEC 62109-1  IP30 (IP31 is optional)  Ind output) (in accordance with IEC 62	us, Alarm ogger  for RM nected  cking (MPPT)  derate above 50°C)
LED LCD COMMUI Selectabl Dry conta SYSTEM Control Femp. co ENVIRON Femperat Relative h Pollution Max. ope DESIGN I Standard ngress p Protective Overvolta DIMENSI Wall mou Rack mon	NICATION INTERFACE le by setting act signal  Impensation range IMENT ture Inumidity degree classification eration altitude REGULATION Intercetion e class age category ON (W x H x D) (apprount case unt case (2U) (approximate in kg.)	Battery le Digita  RS-485 Charge Automatic cod  0 - 50°C (Extended rad  2,0  II (input ar ximate in cm.)  23 x 31  48.2 x 8.9 x 45.3 cm (2U)	evel, PV voltage level, Operation statudent meter, 180 days power and event located (default) or RS-232 for WM, RS-485 er fail and low battery voltage disconstitution oling fan, Maximum Power Point Trace-5 to 7 mV / cell / celsius (option)  Inge: 0 - 70°C) (Output characteristic 0 - 95% (non-condensing)  III  III  IIII  IIII  IIIII  IIIIIIII	us, Alarm ogger  for RM nected  cking (MPPT)  derate above 50°C)  2109-1)  32.3 x 42 x 16 cm  48.2 x 8.9 x 45.3 cm (2U)
ED COMMUI Selectabl Ory conta SYSTEM Control Temp. co ENVIRON Temperat Relative h Pollution Max. ope DESIGN I Standard Ingress p Protective Overvolta DIMENSI Vall mou Rack mon WEIGHT Vall mou	NICATION INTERFACE le by setting act signal  Impensation range IMENT ture Inumidity degree classification eration altitude REGULATION Intercetion e class age category ON (W x H x D) (apprount case unt case (2U) (approximate in kg.)	Battery le Digita  RS-485 Charge  Automatic cod  0 - 50°C (Extended rad  2,0  II (input ar ximate in cm.)	evel, PV voltage level, Operation statul meter, 180 days power and event level (default) or RS-232 for WM, RS-485 or fail and low battery voltage disconstitution oling fan, Maximum Power Point Trace-5 to 7 mV / cell / celsius (option)  nge: 0 - 70°C) (Output characteristic 0 - 95% (non-condensing)  III  000 m / 6,560 feet (without derating)  IEC 61683, IEC 62109-1  IP30 (IP31 is optional)  Ind output) (in accordance with IEC 66)	us, Alarm ogger  for RM nected  cking (MPPT)  derate above 50°C)

Authorized Distributor

LEO ELECTRONICS CO.,LTD.

27, 29 Soi Bangna-Trad Rd 34, Bangna Tai, Bangna, Bangkok 10260 THAILAND Tel. 0-2746-9500 Fax. 0-2746-8712 e-mail : RNE@leonics.com

Authorized Dealer

P.LEN.BRO.CCL.220 Rev.14.00/2022