

FT Pro Series Pure Sine Wave Inverter With Charger

(3KW, 4KW, 5KW, 6KW)

MAIN FEATURES



Comptible to Lead acid battery & Lithium battery



Adjustable LCD screen to set charging current and voltage based on your battery



Product Specifications

Model:FT		3KW	4KW	5KW	6KW
Rated Power		3000W	4000W	5000W	6000W
Battery	Rated Voltage	12VDC/24VDC/48VDC	24VDC/48VDC		48VDC/96VDC
	Charge Current	30A (default) -CO-C6			
	Battery Type	U0-U7			
Input	Voltage Range	85-138VAC/170-275VAC			
	Frequency	45-65Hz			
	Product Size:L"W"H(mm)	486*247*179	555*307*189		
	Package Size: L"W"H(mm)	550*310*230	640*370*240		
Output	Voltage Range	110VAC/220VAC; ±5%(Inversion mode)			
	Frequency	50/60Hz±1%(Inversion mode)			
	Output Wave	Pure Sine Wave			
	Conversion Time	<10ms(Typical load)			
	Efficiency	>85% (80% resistive load)			
	Overload	110-120%/30S; >160%/300ms;			
	Protection Function	Battery overvoltage protection, battery undervoltage protection, overload,protection, short circuit protection, overtemperature protection, etc.			
	Operation Of Ambient Temperature	0-40°C			
Ambient Temperature For Storage	-15-+50°C				
Operation/Storage Ambient	0-90% No Condensation				

P.S.: We keep the right to change without any information.