

BENY Microinverter



ZHEJIANG BENYI NEW ENERGY CO., LTD.

CHANGJIANG RD, WENZHOU DAQIAO INDUSTRY PARK, BEIBAIXIANG TOWN, YUEQING, WENZHOU CITY, ZHEJIANG PROVINCE, CHINA TEL: +86-577-5717 7008 FAX: +86-577-5717 7007

- ⊠ info@beny.com
- @ www.pvb.com
- This catalogue has been printed on ecological paper.
 Zhejiang Benyi New Energy Co., Ltd. All rights reserved.
 If the models and specifications in this product catalogue





VERSION: 20240606-01



Catalogue

Z/BENY



Company Introduction

As a national high-tech enterprise, BENY New Energy is concentrating on developing renewable energy for a sustainable future.

We are a leading brand annually producing hundreds of thousands of quality DC protection products and EV charging stations for complete and reliable solar photovoltaic, battery energy storage, and EV charging system.

Offering solar PV switchgear and solar combiner solutions 1000V 1500V. Newly launch solar panel RSD, solar fire safety switches for higher safety level, microinverter for solar buildings for higher efficiency.

The newest EV charging and energy storage solutions are compatible with solar PV power which is reliable for residential and commercial applications.







We are Working on a Sustainable Future.





20 Million Annual Production Capacity

Catalogue





Microinverter Combination





Monitoring solution

Communication with BENY microinverters through PLCC/Wi-Fi enables users to manage the systems in a smart digital way.



Catalogue





BYM600

Adapted to 60~75-cell or 120~150 half-cell PV modules

Static MPPT efficiency 99.80%

High reliability, IP67 (NEMA 6) enclosure

Description

With the maximum output power of 520VA/570VA/600VA, microinverters connect to 1 module and enable module-level maintenance and management of the PV station by monitoring power generation of each module. Module-level data can be uploaded to the monitoring platform via BENY data transfer units through PLCC/Wi-Fi.

Input Data (DC)			
Model	BYM600		
Recommended input power (Single)	(STC) 400~700+Wp , 60~75-cell/120~150 half-cell		
Recommended input power (Dual)	(STC) (300~450Wp) *2 , 72~75-cell/144~150 half-cell (NMOT) Vmp≥34V and Imp≤12A		
MPPT voltage range	24V~50V		
Operating voltage range	16V~60V		
Maximum input voltage	60V		
Max. short circuit current	24A		
Max. input current	20A		
Output Data (AC)			
Rated output power	600VA		
Maximum output power	600VA (Vac≽220,Vmp≽33)		
Rated voltage (range)	230V (176V~265V)		
Rated frequency (range)	50Hz/60Hz [46.5Hz~62Hz]		
Maximum continuous output current	2.73A		
Maximum harmonic distortion	<4%		
Power factor	>0.99 (Default)		
Maximum connection number in one string (PLCC) (30A circuit breaker, 10AWG cable)	10 units		
Maximum connection number in one string (Wi-Fi) (40A circuit breaker, 10AWG cable)	14 units		
Efficiency			
Peak efficiency	96.5%		
MPPT efficiency	>99.8%		
Night power consumption	<100mW		
Other Parameters			
Communication method	PLCC/Bluetooth+Wi-Fi (Optional)		
Safety protection	Class I		
Enclosure rating	IP67		
Operating temperature	-40°C to +70°C		
Storage temperature	-40°C to +85°C		
Relative humidity	0~98%		
Transformer design	High frequency transformer, Electrical isolated		
Overvoltage class	OVC III (AC), OVC II (PV)		
Warranty period	12 / 25 years (Optional)		
Dimensions (L*W*H mm)	210*230*34		
Weight (kg)	2.39		
Safety regulations	IEC/EN 61000-6, CISPR11+A1+A2, IEC/EN 62109-1/2, EN 505491:2019 VE AR-N 4105:2018/DIN VDE 0124:2020, AS 4777.2 :2020, INMETRO, UTE C 712-1/DIN VDE 0126/VFR 2019, G98, CEI 021:2020, NC RFG, NTS DAKKS		

B١	M	60	0

DE-:15-5.

Catalogue

B

 MI AC Bus
 DC cable
 Wi-Fi signal
 Ethernet
 Internet

